

# PKCELL

# 8145

## Operation Instruction

1. Put the battery in the charger with the correct polarity.
2. Insert the charger into the socket of Corresponding AC220V-50Hz power supply.
3. The red LED shows that the corresponding battery is charging.
4. Please take the timetable of charge as a reference, do take out the battery in time.

## Charger Characteristics

- Two channels in series, fast and slow charging optional.
- Capable to charge 2/4pcs of AA/AAA, 1-2pcs of 6F22(9V) Ni-MH/Ni-Cd rechargeable batteries.
- Specially designed for the digital camera, walkman, power-driven toy, PDA and so on.

## Technical Parameter

Input: AC220V 50HZ  
Output: DC AA 2X1.2V 200mA  
          AAA 2X1.2V 100mA  
          9V 30mA

## Attention


1. For indoors use only. Don't lay the charger in the environment of dampness or high temperature.
2. Pull out the charger from the socket if long time on use.
3. Primary batteries/recharged batteries not allowed to charge in the charger, liquid leaking or exploding otherwise.

## Timetable of charge

Type	Capacity	Time(h)	Type	Capacity	Time(h)
AA-NiMH	2500mAh	15h	AA-NiCd	700mAh	4h
AA-NiMH	2000mAh	12h	AA-NiMH	600mAh	7h
AA-NiMH	1800mAh	10h	AA-NiCd	380mAh	5h
AA-NiMH	1600mAh	9h	9V-NiCd	120mAh	5h
AA-NiMH	1300mAh	8h	9V-NiCd	100mAh	4h
AA-NiCd	800mAh	5h			



www.pkcell.net



Only when 2pcs of AA/AAA batteries are put into Group A or Group B, the corresponding LED light will be on.

## Safety Guarantee

Conforming to CE standard

